

Pin List: XEM7001

2019-01-22

Connector	Pin	FPGA Pin	Description
JP1	1		+3.3VDD
JP1	2		+3.3VDD
JP1	3	H1	I/O
JP1	4	H2	I/O
JP1	5	G1	I/O
JP1	6	G2	I/O
JP1	7	F2	I/O
JP1	8	E1	I/O
JP1	9	E2	I/O
JP1	10	D1	I/O
JP1	11	C1	I/O
JP1	12	C2	I/O
JP1	13	B1	I/O
JP1	14	B2	I/O
JP1	15	A2	I/O
JP1	16	A3	I/O
JP1	17	D4	I/O / MRCCp
JP1	18	C4	I/O / MRCCn
JP1	19		DGND
JP1	20		DGND
JP2	1		DGND
JP2	2		DGND
JP2	3		SYS CLK 5
JP2	4	P10	I/O / SRCC
JP2	5	J1	I/O
JP2	6	J3	I/O
JP2	7	K2	I/O
JP2	8	K1	I/O
JP2	9		+3.3VDD
JP2	10		+3.3VDD
JP2	11	L2	I/O

Connector	Pin	FPGA Pin	Description
JP2	12	K3	I/O
JP2	13	L3	I/O
JP2	14	M1	I/O
JP2	15	M2	I/O
JP2	16	L4	I/O
JP2	17	M4	I/O
JP2	18	N1	I/O
JP2	19		DGND
JP2	20		DGND
JP2	21	N2	I/O
JP2	22	N3	I/O
JP2	23	P1	I/O
JP2	24	R1	I/O
JP2	25	R2	I/O
JP2	26	P3	I/O
JP2	27	T2	I/O
JP2	28	R3	I/O
JP2	29	T3	I/O
JP2	30	N4	I/O
JP2	31		DGND
JP2	32		DGND
JP2	33	P4	I/O
JP2	34	T4	I/O
JP2	35	P5	I/O
JP2	36	N6	I/O
JP2	37	R5	I/O
JP2	38	P8	I/O
JP2	39	T5	I/O
JP2	40	R6	I/O
JP2	41		+3.3VDD
JP2	42		+3.3VDD
JP2	43	T9	I/O
JP2	44	R7	I/O
JP2	45	T7	I/O

Connector	Pin	FPGA Pin	Description
JP2	46	R8	I/O
JP2	47	T8	I/O
JP2	48	T10	I/O
JP2	49		DGND
JP2	50		DGND
JP3	1		DGND
JP3	2		DGND
JP3	3	A8	I/O
JP3	4	D9	I/O
JP3	5	C8	I/O
JP3	6	D10	I/O
JP3	7	A9	I/O
JP3	8	C9	I/O
JP3	9		+3.3VDD
JP3	10		+3.3VDD
JP3	11	B9	I/O
JP3	12	A10	I/O
JP3	13	B10	I/O
JP3	14	C11	I/O / SRCC
JP3	15	B12	I/O
JP3	16	A12	I/O
JP3	17	C12	I/O
JP3	18	F13	I/O
JP3	19		DGND
JP3	20		DGND
JP3	21	A13	I/O
JP3	22	A14	I/O
JP3	23	E13	I/O
JP3	24	B14	I/O
JP3	25	C14	I/O
JP3	26	A15	I/O
JP3	27	B15	I/O
JP3	28	B16	I/O
JP3	29	C16	I/O

Connector	Pin	FPGA Pin	Description
JP3	30	D15	I/O
JP3	31		DGND
JP3	32		DGND
JP3	33	D16	I/O
JP3	34	D14	I/O
JP3	35	E16	I/O
JP3	36	E15	I/O
JP3	37	G15	I/O
JP3	38	F14	I/O
JP3	39	H14	I/O
JP3	40	G16	I/O
JP3	41		+3.3VDD
JP3	42		+3.3VDD
JP3	43	H13	I/O
JP3	44	H16	I/O
JP3	45	F15	I/O
JP3	46	G14	I/O
JP3	47	E12	I/O / MRCC
JP3	48		SYS CLK 4
JP3	49		DGND
JP3	50		DGND